


## RECTIFIER, CONTROL, AND FILAMENT TRANSFORMERS (CON'T)


### WITH SINGLE SECONDARY

Mfr. No.	Secondary Volts	Secondary Amps	Test Volts (rms)	Primary Volts	Terminations	Mtg. Style	Size, Inches H x W x D
P-8357‡	25.2 CT	2.0	1500	117	Leads	A	2½ × 4 × 2¼
P-8574	25.2 CT	2.0	1500	115/230	Leads	A	2½ × 4 × 2¼
P-8388	25.2 CT	2.8	1500	117	Leads	A	2½ × 4 × 2¼
P-8645	25.2 CT	5.0	1500	117	Leads	C	4¼ × 3⅞ × 3⅞
P-8607	26.0 CT	0.25	2500	117	Leads	A	1½ × 2⅞ × 1¼
P-8609	26.8 CT	1.0	1500	117	Leads	A	2 × 3¼ × 2½
P-8600	28.0 CT	0.09	1500	117	Leads	A	1¼ × 2½ × 1¼
P-8601	28.0 CT	0.18	1500	117	Leads	A	1¾ × 2¾ × 1¾
P-8602	28.0 CT	0.3	1500	117	Leads	A	1¾ × 2¾ × 1¾
P-8603‡	28.0 CT	0.8	1500	117	Leads	A	2 × 3¼ × 2½
P-8667	28.0 CT	1.0	1500	117	Leads	A	2 × 3¼ × 2½
P-8668	28.0 CT	2.0	1500	117	Leads	NV	3⅞ × 2½ × 2½
P-8669	28.0 CT	4.0	1500	117	Leads	NV	3⅞ × 3⅞ × 3¼
P-8670	28.0 CT	6.0	1500	117	Leads	NV	4⅞ × 3⅞ × 3½
P-8610	36.0 CT	0.07	1500	117	Leads	A	1¼ × 2½ × 1¼
P-8611	36.0 CT	0.14	1500	117	Leads	A	1¾ × 2¾ × 1¾
P-8612	36.0 CT	0.3	1500	117	Leads	A	1¾ × 2¾ × 1¾
P-8613	36.0 CT	0.55	1500	117	Leads	A	2 × 3¼ × 1¾
P-8671	36.0 CT	1.0	1500	117	Leads	A	2½ × 3¾ × 2¼
P-8672	36.0 CT	2.0	1500	117	Leads	NV	3⅞ × 2½ × 2½
P-8673	36.0 CT	4.0	1500	117	Leads	NV	4⅞ × 3⅞ × 2¾
P-8674	36.0 CT	6.0	1500	117	Leads	NV	4⅞ × 3¾ × 3½
P-8542	40.0 CT	0.25	2500	115/230	Leads	A	1½ × 2⅞ × 1½
P-8564	40.0 CT	1.0	1500	115	Leads	A	2½ × 4 × 2¼
P-8566	40.0 CT	4.0	1500	115	Leads	NV	3¾ × 3¾ × 3½
P-8605	48.0 CT	1.0	2500	117	Leads	A	2½ × 4 × 2½


‡ U.L. Recognized.




Mtg. Style "NV"




Mtg. Style "A"



Mtg. Style "S"



Mtg. Style "LB"



Mtg. Style "C"

### UNIVERSAL CONTROL/RECTIFIER TRANSFORMERS

For 50/60 Hz. but may be operated from a 400 Hz source with no change in output ratings. By connecting primaries in series (for 230 volts) but using only 115 V input, a series of half-voltage output ratings becomes available at full rated current from each secondary. Solder lug termination.

Mfr. No.	Mtg. Style	Secondary Ratings Parallel	Secondary Ratings Series	VA
P-6375	S	6.0 V at 2.0 A	12.0 VCT at 1.0 A	12
P-6376	S	6.0 V at 4.0 A	12.0 VCT at 2.0 A	24
P-6377	S	12.0 V at 4.0 A	24.0 VCT at 2.0 A	48
P-6378	NV	12.0 V at 8.0 A	24.0 VCT at 4.0 A	96
P-6379	NV	12.0 V at 16.0 A	24.0 VCT at 8.0 A	192
P-8615	S	24.0 V at 0.5 A	48.0 VCT at 0.25 A	12
P-8616	S	24.0 V at 1.0 A	48.0 VCT at 0.5 A	24
P-8617	S	24.0 V at 2.0 A	48.0 VCT at 1.0 A	48
P-8618	NV	24.0 V at 4.0 A	48.0 VCT at 2.0 A	96
P-8619	NV	24.0 V at 8.0 A	48.0 VCT at 4.0 A	192

### LOW BOY™ LOW-PROFILE POWER TRANSFORMERS (CASE STYLE "LB")

Primaries are dual 115/230, 50/60 Hz.

Mfr. No.	Secondary Ratings Parallel	Secondary Ratings Series	VA	Size, Inches H x W x D
LB210	5.0 V at 0.4 A	10.0 VCT at 0.2 A	2	0.625 × 1.562 × 1.875
LB310	5.0 V at 0.6 A	10.0 VCT at 0.3 A	2	0.625 × 1.562 × 1.875
LB215	7.5 V at 0.3 A	15.0 VCT at 0.15 A	3	0.625 × 1.562 × 1.875
LB240	20.0 V at 0.12 A	40.0 VCT at 0.06 A	2	0.625 × 1.562 × 1.875
LB256	28.0 V at 0.09 A	56.0 VCT at 0.045 A	2	0.625 × 1.562 × 1.875
LB288	44.0 V at 0.056 A	88.0 VCT at 0.028 A	2	0.625 × 1.562 × 1.875
LB2120	60.0 V at 0.04 A	120.0 VCT at 0.02 A	2	0.625 × 1.562 × 1.875
LB2230	115.0 V at 0.02 A	230.0 VCT at 0.01 A	2	0.625 × 1.562 × 1.875
LB315	7.5 V at 0.45 A	15.0 VCT at 0.225 A	3	0.625 × 1.562 × 1.875
LB410	5.0 V at 0.8 A	10.0 VCT at 0.4 A	4	0.875 × 1.562 × 1.875
LB510	5.0 V at 1.0 A	10.0 VCT at 0.5 A	5	0.875 × 1.562 × 1.875
LB412	6.0 V at 0.667 A	12.0 VCT at 0.333 A	4	0.875 × 1.562 × 1.875
LB512	6.0 V at 0.833 A	12.0 VCT at 0.417 A	5	0.875 × 1.562 × 1.875
LB420	10.0 V at 0.4 A	20.0 VCT at 0.2 A	4	0.875 × 1.562 × 1.875
LB520	10.0 V at 0.5 A	20.0 VCT at 0.25 A	5	0.875 × 1.562 × 1.875
LB424	12.0 V at 0.333 A	24.0 VCT at 0.167 A	4	0.875 × 1.562 × 1.875
LB524	12.0 V at 0.417 A	24.0 VCT at 0.208 A	5	0.875 × 1.562 × 1.875
LB4120	60.0 V at 0.066 A	120.0 VCT at 0.033 A	4	0.875 × 1.562 × 1.875
LB5120	60.0 V at 0.084 A	120.0 VCT at 0.042 A	5	0.875 × 1.562 × 1.875
LB610	5.0 V at 1.2 A	10.0 VCT at 0.6 A	6	0.875 × 1.562 × 1.875
LB1210	5.0 V at 2.4 A	10.0 VCT at 1.2 A	12	1.062 × 2.000 × 2.500
LB612	6.3 V at 0.9 A	12.6 VCT at 0.45 A	6	0.875 × 1.562 × 1.875
LB1212	6.3 V at 1.8 A	12.6 VCT at 0.9 A	12	1.062 × 2.000 × 2.500
LB616	8.0 V at 0.7 A	16.0 VCT at 0.35 A	6	0.875 × 1.562 × 1.875
LB1216	8.0 V at 1.4 A	16.0 VCT at 0.7 A	12	1.062 × 2.000 × 2.500
LB620	10.0 V at 0.6 A	20.0 VCT at 0.3 A	6	0.875 × 1.562 × 1.875
LB1220	10.0 V at 1.2 A	20.0 VCT at 0.6 A	12	1.062 × 2.000 × 2.500
LB624	12.0 V at 0.5 A	24.0 VCT at 0.25 A	6	0.875 × 1.562 × 1.875
LB1224	12.0 V at 1.0 A	24.0 VCT at 0.5 A	12	1.062 × 2.000 × 2.500
LB634	17.0 V at 0.34 A	34.0 VCT at 0.17 A	6	0.875 × 1.562 × 1.875
LB1234	17.0 V at 0.68 A	34.0 VCT at 0.34 A	12	1.062 × 2.000 × 2.500
LB640	20.0 V at 0.3 A	40.0 VCT at 0.15 A	6	0.875 × 1.562 × 1.875
LB1240	20.0 V at 0.6 A	40.0 VCT at 0.3 A	12	1.062 × 2.000 × 2.500
LB656	28.0 V at 0.2 A	56.0 VCT at 0.1 A	6	0.875 × 1.562 × 1.875
LB1256	28.0 V at 0.4 A	56.0 VCT at 0.2 A	12	1.062 × 2.000 × 2.500
LB688	44.0 V at 0.13 A	88.0 VCT at 0.065 A	6	0.875 × 1.562 × 1.875
LB1288	44.0 V at 0.26 A	88.0 VCT at 0.13 A	12	1.062 × 2.000 × 2.500
LB6120	60.0 V at 0.1 A	120.0 VCT at 0.05 A	6	0.875 × 1.562 × 1.875
LB12120	60.0 V at 0.2 A	120.0 VCT at 0.1 A	12	1.062 × 2.000 × 2.500
LB6230	115.0 V at 0.05 A	230.0 VCT at 0.025 A	6	0.875 × 1.562 × 1.875
LB12230	115.0 V at 0.1 A	230.0 VCT at 0.05 A	12	1.062 × 2.000 × 2.500

# 16

# TRANSFORMERS & REACTORS