



RECTIFIER, CONTROL, AND FILAMENT TRANSFORMERS

WITH SINGLE SECONDARY


All primaries 50/60 Hz. May be operated from a 400 Hz source with no change in output rating. All secondary voltages $\pm 3\%$. Insulation test voltage is twice allowable rms working voltage plus 1000 volts.




Mtg. Style "A"



Mtg. Style "C"



Mtg. Style "NV"



Mtg. Style "S"

Mfr. No.	Secondary Volts	Secondary Amps	Test Volts (rms)	Primary Volts	Terminations	Mtg. Style	Size, Inches H x W x D
P-8629	2.5	1.0	1500	117	Leads	A	1 3/8 x 2 3/8 x 1 3/8
P-4026	2.5	1.5	2500	117	Leads	A	1 1/8 x 2 7/8 x 1 1/8
P-6133†	2.5 CT	5.0	7500	117	Leads	S	2 3/4 x 3 1/8 x 2 1/4
P-6454	2.5 CT	10.0	7500	117/107	Leads	S	3 1/8 x 3 3/8 x 2 1/2
P-6467	5.0 CT	3.0	2500	117	Leads	A	2 x 3 1/4 x 2 1/8
P-6135	5.0 CT	10.0	2500	117	Leads	NV	3 1/8 x 2 1/2 x 2 3/4
P-8385	6.3 CT	0.3	1500	117	Leads	A	1 1/4 x 2 1/8 x 1 1/8
P-6465‡	6.3 CT	0.6	1500	117	Leads	A	1 3/8 x 2 3/8 x 1 1/2
P-8705	6.3 CT	0.6	1500	230	Leads	A	1 3/8 x 2 3/8 x 1 1/2
P-8389‡	6.3	1.0	1500	117	Leads	A	1 1/8 x 2 7/8 x 1 1/8
P-6134‡	6.3 CT	1.2	3000	117	Leads	A	1 1/8 x 2 7/8 x 1 1/8
P-8190	6.3	1.2	5000	117	Leads	A	2 x 3 1/4 x 1 1/8
P-6466	6.3 CT	3.0	2500	117	Leads	A	2 x 3 1/4 x 2 1/8
P-8648	6.3 CT	4.0	1500	117	Leads	A	2 3/8 x 3 3/4 x 2 1/8
P-8649	6.3 CT	5.0	1500	117	Leads	A	2 3/8 x 3 3/4 x 2 1/8
P-3064†	6.3 CT	6.0	2500	117	Lugs	NV	3 1/8 x 2 1/2 x 2 3/8
P-6456	6.3 CT	6.0	2000	117/107	Leads	A	2 3/8 x 3 3/4 x 2 3/8
P-8651	6.3 CT	8.0	1500	117	Leads	A	2 3/8 x 4 x 2 1/8
P-6464	6.3 CT	10.0	2000	117	Leads	C	3 1/2 x 2 13/16 x 3 1/4
P-6308†	6.3 CT	10.0	2500	117/107	Leads	NV	3 3/16 x 2 11/16 x 2 3/8
P-6309	6.3 CT	20.0	2500	117/107	Leads	NV	4 9/16 x 3 3/4 x 3 3/8
P-5015†	7.5 CT	4.0	2500	117	Lugs	NV	3 1/8 x 2 1/2 x 2 1/4
P-6138†	7.5 CT	8.0	2500	117	Leads	NV	3 1/8 x 3 3/8 x 2 3/4
P-8652	10.0 CT	1.0	1500	117	Leads	A	2 x 3 1/4 x 1 1/8
P-8653	10.0 CT	2.0	1500	117	Leads	A	2 x 3 1/4 x 2
P-8380	10.0 CT	3.0	1500	117	Leads	A	2 3/8 x 3 3/4 x 2 1/4
P-8654	10.0 CT	4.0	1500	117	Leads	A	2 3/8 x 4 x 2 1/8
P-5016†	10.0 CT	4.0	2500	117	Lugs	NV	3 7/16 x 2 13/16 x 2 1/2
P-6458	10.0 CT	5.0	2000	117/107	Leads	NV	3 1/8 x 2 1/2 x 2 1/8
P-8655	10.0 CT	8.0	1500	117	Leads	NV	3 1/8 x 2 1/2 x 2 3/8
P-8656	10.0 CT	8.0	1500	117	Leads	NV	3 7/16 x 2 13/16 x 3
P-6461	10.0 CT	10.0	2000	117	Leads	C	3 7/8 x 3 1/4 x 3 3/16
P-8390‡	12.0	0.15	1500	117	Leads	A	1 1/4 x 2 3/8 x 1 1/4
P-8391	12.0	0.35	1500	117	Leads	A	1 3/8 x 2 3/8 x 1 3/8
P-8392‡	12.0	0.70	1500	117	Leads	A	1 1/8 x 2 7/8 x 1 1/8
P-8393	12.0	1.2	1500	117	Leads	A	2 x 3 1/4 x 1 1/8
P-8657	12.0	2.0	1500	117	Leads	A	2 x 3 1/4 x 2 1/8
P-8658	12.0	4.0	1500	117	Leads	A	2 3/8 x 4 x 2 1/4
P-8659	12.0	6.0	1500	117	Leads	NV	3 7/16 x 2 13/16 x 2 3/8
P-8660	12.0	8.0	1500	117	Leads	NV	3 3/16 x 3 1/8 x 2 3/4
P-8384	12.6 CT	1.0	1500	117	Leads	A	2 x 3 1/4 x 1 3/4
P-8550	12.6 CT	1.5	1500	115	Leads	A	1 1/8 x 3 3/16 x 2
P-8130‡	12.6 CT	2.0	1500	117	Leads	A	2 x 3 1/4 x 2 1/8
P-8715	12.6 CT	2.0	1500	230	Leads	A	2 x 3 1/4 x 2 1/8
P-8358	12.6 CT	3.0	1500	117	Leads	A	2 3/8 x 3 3/4 x 2 1/4
P-8641	12.6 CT	4.0	1500	117	Leads	A	2 3/8 x 4 x 2 3/8
P-8716	12.6 CT	4.0	2500	230	Leads	A	2 3/8 x 4 x 2 3/8
P-8642	12.6 CT	6.0	1500	117	Leads	C	3 1/2 x 2 13/16 x 3 3/8
P-8644	12.6 CT	10.0	1500	117	Leads	C	4 1/4 x 3 7/16 x 3 3/8
P-8577	14.0 CT	0.25	1500	115/230	Leads	A	1 3/8 x 2 3/8 x 1 1/2
P-8553	14.0 CT	0.25	1500	115	Leads	A	1 3/8 x 2 3/8 x 1 1/8
P-8555	14.0 CT	1.0	1500	115	Leads	A	1 11/16 x 3 1/4 x 1 3/4
P-8556	14.0 CT	2.0	1500	115	Leads	A	2 1/4 x 3 11/16 x 1 11/16
P-8557	14.0 CT	4.0	1500	115	Leads	NV	3 x 2 1/2 x 2 7/16
P-8558	14.0 CT	6.0	1500	115	Leads	NV	3 3/8 x 2 13/16 x 2 7/8
P-8690	18.0 CT	0.75	1500	115	Leads	A	1 11/16 x 3 3/16 x 2
P-8691	18.0 CT	1.0	1500	115	Leads	A	1 11/16 x 3 3/16 x 2 1/8
P-8692	18.0 CT	1.5	1500	115	Leads	A	2 3/32 x 3 3/4 x 2 1/8
P-8693	18.0 CT	2.0	1500	115	Leads	A	2 3/32 x 3 3/4 x 2 1/4
P-8500	20.0 CT	0.05	2500	115/230	Leads	A	1 1/4 x 2 1/8 x 1 1/4
P-8504	20.0 CT	0.25	2500	115/230	Leads	A	1 3/8 x 2 3/8 x 1 3/8
P-8505	20.0 CT	0.3	2500	115/230	Leads	A	1 3/8 x 2 3/8 x 1 3/8
P-8507	20.0 CT	0.5	2500	115/230	Leads	A	1 3/8 x 2 7/8 x 1 1/2
P-8508	20.0 CT	1.0	2500	115/230	Leads	A	2 x 3 1/4 x 2 1/4
P-8604‡	20.0 CT	1.0	1500	117	Leads	A	2 x 3 1/4 x 2 1/8
P-8559	20.0 CT	2.0	1500	115	Leads	NV	2 3/16 x 4 x 2 1/4
P-8560	20.0 CT	4.0	1500	115	Leads	NV	3 3/8 x 2 13/16 x 2 7/8
P-8551*	24.0	1.0	1500	115	Leads	A	1 11/16 x 3 1/4 x 2 1/8
P-8694*	24.0	2.0	1500	115	Leads	A	2 3/16 x 4 x 2
P-8394	24.0 CT	0.09	1500	117	Leads	A	1 1/4 x 2 1/8 x 1 1/4
P-8720	24.0 CT	0.09	1500	230	Leads	A	1 1/4 x 2 1/8 x 1 1/4
P-8395‡	24.0 CT	0.2	1500	117	Leads	A	1 3/8 x 2 3/8 x 1 3/8
P-8721	24.0 CT	.200	1500	230	Leads	A	1 3/8 x 2 3/8 x 1 3/8
P-8578	24.0 CT	0.2	1500	115/230	Leads	A	1 3/8 x 2 3/8 x 1 1/2
P-8396‡	24.0 CT	0.4	1500	117	Leads	A	1 3/8 x 2 7/8 x 1 1/8
P-8722	24.0 CT	.400	1500	230	Leads	A	1 3/8 x 2 7/8 x 1 1/2
P-8397‡	24.0 CT	0.7	1500	117	Leads	A	2 x 3 1/4 x 1 3/4
P-8723	24.0 CT	.700	1500	230	Leads	A	2 x 3 1/4 x 1 1/8
P-8661	24.0 CT	1.0	1500	117	Leads	A	2 x 3 1/4 x 2 1/8
P-8575	24.0 CT	1.0	1500	115/230	Leads	A	1 11/16 x 3 3/16 x 2
P-8662	24.0 CT	2.0	1500	117	Leads	A	2 3/8 x 4 x 2 3/8
P-8663‡	24.0 CT	4.0	1500	117	Leads	NV	3 13/16 x 3 1/8 x 2 13/16
P-8664	24.0 CT	6.0	1500	117	Leads	NV	4 3/16 x 3 7/16 x 3
P-8665	24.0 CT	8.0	1500	117	Leads	NV	4 3/16 x 3 7/16 x 3 3/8
P-8695	24.0 CT	10.0	1500	115	Leads	NV	4 3/8 x 3 7/16 x 3 3/4
P-8666‡	24.0 CT	12.0	1500	117	Leads	NV	4 3/8 x 3 3/4 x 4 3/8
P-6469	25.2	1.0	1500	117	Leads	A	2 x 3 1/4 x 2 1/8
P-8707	25.2	1.0	1500	230	Leads	A	2 x 3 1/4 x 2 1/8
P-8180	25.2 CT	1.0	1500	117	Leads	A	2 x 3 1/4 x 2 1/4

* 60 Hz only.

† Has electrostatic shield.

‡ U.L. Recognized.

LISTING CONTINUED ON FOLLOWING PAGE

RECTIFIER, CONTROL, AND FILAMENT TRANSFORMERS (CON'T)

WITH SINGLE SECONDARY

Mfr. No.	Secondary Volts	Secondary Amps	Test Volts (rms)	Primary Volts	Terminations	Mtg. Style	Size, Inches H x W x D
P-8357‡	25.2 CT	2.0	1500	117	Leads	A	2 1/2 x 4 x 2 1/4
P-8574	25.2 CT	2.0	1500	115/230	Leads	A	2 1/2 x 4 x 2 1/4
P-8388	25.2 CT	2.8	1500	117	Leads	A	2 1/2 x 4 x 2 1/4
P-8645	25.2 CT	5.0	1500	117	Leads	C	4 1/4 x 3 1/8 x 3 1/8
P-8607	26.0 CT	0.25	2500	117	Leads	A	1 1/2 x 2 1/8 x 1 1/4
P-8609	26.8 CT	1.0	1500	117	Leads	A	2 x 3 1/4 x 2 1/8
P-8600	28.0 CT	0.09	1500	117	Leads	A	1 1/4 x 2 1/8 x 1 1/4
P-8601	28.0 CT	0.18	1500	117	Leads	A	1 3/8 x 2 3/8 x 1 3/8
P-8602	28.0 CT	0.3	1500	117	Leads	A	1 1/2 x 2 1/8 x 1 1/8
P-8603‡	28.0 CT	0.8	1500	117	Leads	A	2 x 3 1/4 x 2 1/8
P-8667	28.0 CT	1.0	1500	117	Leads	A	2 x 3 1/4 x 2 1/8
P-8668	28.0 CT	2.0	1500	117	Leads	NV	3 1/8 x 2 1/2 x 2 1/2
P-8669	28.0 CT	4.0	1500	117	Leads	NV	3 1/8 x 3 1/8 x 3 1/8
P-8670	28.0 CT	6.0	1500	117	Leads	NV	4 1/8 x 3 1/8 x 3 1/2
P-8610	36.0 CT	0.07	1500	117	Leads	A	1 1/4 x 2 1/8 x 1 1/4
P-8611	36.0 CT	0.14	1500	117	Leads	A	1 3/8 x 2 3/8 x 1 3/8
P-8612	36.0 CT	0.3	1500	117	Leads	A	1 1/2 x 2 1/8 x 1 1/8
P-8613	36.0 CT	0.55	1500	117	Leads	A	2 x 3 1/4 x 1 1/8
P-8671	36.0 CT	1.0	1500	117	Leads	A	2 1/2 x 3 1/4 x 2 1/4
P-8672	36.0 CT	2.0	1500	117	Leads	NV	3 1/8 x 2 1/8 x 2 3/4
P-8673	36.0 CT	4.0	1500	117	Leads	NV	4 1/8 x 3 1/8 x 2 1/8
P-8674	36.0 CT	6.0	1500	117	Leads	NV	4 1/8 x 3 1/4 x 3 1/2
P-8542	40.0 CT	0.25	2500	115/230	Leads	A	1 1/2 x 2 1/8 x 1 1/2
P-8564	40.0 CT	1.0	1500	115	Leads	A	2 1/8 x 4 x 2 1/4
P-8566	40.0 CT	4.0	1500	115	Leads	NV	3 1/4 x 3 1/8 x 3 1/2
P-8605	48.0 CT	1.0	2500	117	Leads	A	2 1/2 x 4 x 2 1/8

‡ U.L. Recognized.

UNIVERSAL CONTROL/RECTIFIER TRANSFORMERS

For 50/60 Hz. but may be operated from a 400 Hz source with no change in output ratings. By connecting primaries in series (for 230 volts) but using only 115 V input, a series of half-voltage output ratings becomes available at full rated current from each secondary. Solder lug termination.

Mfr. No.	Mtg. Style	Secondary Ratings Parallel	Secondary Ratings Series	VA
P-6375	S	6.0 V at 2.0 A	12.0 VCT at 1.0 A	12
P-6376	S	6.0 V at 4.0 A	12.0 VCT at 2.0 A	24
P-6377	S	12.0 V at 4.0 A	24.0 VCT at 2.0 A	48
P-6378	NV	12.0 V at 8.0 A	24.0 VCT at 4.0 A	96
P-6379	NV	12.0 V at 16.0 A	24.0 VCT at 8.0 A	192
P-8615	S	24.0 V at 0.5 A	48.0 VCT at 0.25 A	12
P-8616	S	24.0 V at 1.0 A	48.0 VCT at 0.5 A	24
P-8617	S	24.0 V at 2.0 A	48.0 VCT at 1.0 A	48
P-8618	NV	24.0 V at 4.0 A	48.0 VCT at 2.0 A	96
P-8619	NV	24.0 V at 8.0 A	48.0 VCT at 4.0 A	192


LOW BOY™ LOW-PROFILE POWER TRANSFORMERS (CASE STYLE "LB")

Primaries are dual 115/230, 50/60 Hz.


Mfr. No.	Secondary Ratings Parallel	Secondary Ratings Series	VA	Size, Inches H x W x D
LB210	5.0 V at 0.4 A	10.0 VCT at 0.2 A	2	0.625 x 1.562 x 1.875
LB310	5.0 V at 0.6 A	10.0 VCT at 0.3 A	3	0.625 x 1.562 x 1.875
LB215	7.5 V at 0.3 A	15.0 VCT at 0.15 A	2	0.625 x 1.562 x 1.875
LB240	20.0 V at 0.12 A	40.0 VCT at 0.06 A	2	0.625 x 1.562 x 1.875
LB256	28.0 V at 0.09 A	56.0 VCT at 0.045 A	2	0.625 x 1.562 x 1.875
LB288	44.0 V at 0.056 A	88.0 VCT at 0.028 A	2	0.625 x 1.562 x 1.875
LB2120	60.0 V at 0.04 A	120.0 VCT at 0.02 A	2	0.625 x 1.562 x 1.875
LB2230	115.0 V at 0.02 A	230.0 VCT at 0.01 A	2	0.625 x 1.562 x 1.875
LB315	7.5 V at 0.45 A	15.0 VCT at 0.225 A	3	0.625 x 1.562 x 1.875
LB410	5.0 V at 0.8 A	10.0 VCT at 0.4 A	4	0.875 x 1.562 x 1.875
LB510	5.0 V at 1.0 A	10.0 VCT at 0.5 A	5	0.875 x 1.562 x 1.875
LB412	6.0 V at 0.667 A	12.0 VCT at 0.333 A	4	0.875 x 1.562 x 1.875
LB512	6.0 V at 0.833 A	12.0 VCT at 0.417 A	5	0.875 x 1.562 x 1.875
LB420	10.0 V at 0.4 A	20.0 VCT at 0.2 A	4	0.875 x 1.562 x 1.875
LB520	10.0 V at 0.5 A	20.0 VCT at 0.25 A	5	0.875 x 1.562 x 1.875
LB424	12.0 V at 0.333 A	24.0 VCT at 0.167 A	4	0.875 x 1.562 x 1.875
LB524	12.0 V at 0.417 A	24.0 VCT at 0.208 A	5	0.875 x 1.562 x 1.875
LB4120	60.0 V at 0.066 A	120.0 VCT at 0.033 A	4	0.875 x 1.562 x 1.875
LB5120	60.0 V at 0.084 A	120.0 VCT at 0.042 A	5	0.875 x 1.562 x 1.875
LB610	5.0 V at 1.2 A	10.0 VCT at 0.6 A	6	0.875 x 1.562 x 1.875
LB1210	5.0 V at 2.4 A	10.0 VCT at 1.2 A	12	1.062 x 2.000 x 2.500
LB612	6.3 V at 0.9 A	12.6 VCT at 0.45 A	6	0.875 x 1.562 x 1.875
LB1212	6.3 V at 1.8 A	12.6 VCT at 0.9 A	12	1.062 x 2.000 x 2.500
LB616	8.0 V at 0.7 A	16.0 VCT at 0.35 A	6	0.875 x 1.562 x 1.875
LB1216	8.0 V at 1.4 A	16.0 VCT at 0.7 A	12	1.062 x 2.000 x 2.500
LB620	10.0 V at 0.6 A	20.0 VCT at 0.3 A	6	0.875 x 1.562 x 1.875
LB1220	10.0 V at 1.2 A	20.0 VCT at 0.6 A	12	1.062 x 2.000 x 2.500
LB624	12.0 V at 0.5 A	24.0 VCT at 0.25 A	6	0.875 x 1.562 x 1.875
LB1224	12.0 V at 1.0 A	24.0 VCT at 0.5 A	12	1.062 x 2.000 x 2.500
LB634	17.0 V at 0.34 A	34.0 VCT at 0.17 A	6	0.875 x 1.562 x 1.875
LB1234	17.0 V at 0.68 A	34.0 VCT at 0.34 A	12	1.062 x 2.000 x 2.500
LB640	20.0 V at 0.3 A	40.0 VCT at 0.15 A	6	0.875 x 1.562 x 1.875
LB1240	20.0 V at 0.6 A	40.0 VCT at 0.3 A	12	1.062 x 2.000 x 2.500
LB656	28.0 V at 0.2 A	56.0 VCT at 0.1 A	6	0.875 x 1.562 x 1.875
LB1256	28.0 V at 0.4 A	56.0 VCT at 0.2 A	12	1.062 x 2.000 x 2.500
LB688	44.0 V at 0.13 A	88.0 VCT at 0.065 A	6	0.875 x 1.562 x 1.875
LB1288	44.0 V at 0.26 A	88.0 VCT at 0.13 A	12	1.062 x 2.000 x 2.500
LB6120	60.0 V at 0.1 A	120.0 VCT at 0.05 A	6	0.875 x 1.562 x 1.875
LB12120	60.0 V at 0.2 A	120.0 VCT at 0.1 A	12	1.062 x 2.000 x 2.500
LB6230	115.0 V at 0.05 A	230.0 VCT at 0.025 A	6	0.875 x 1.562 x 1.875
LB12230	115.0 V at 0.1 A	230.0 VCT at 0.05 A	12	1.062 x 2.000 x 2.500

16


TRANSFORMERS & REACTORS




Mtg. Style "NV"




Mtg. Style "A"



Mtg. Style "S"



Mtg. Style "LB"



Mtg. Style "C"

CONTROL TRANSFORMERS

Designed for microprocessor power and logic circuits.

DUAL C.T. SECONDARIES: ALL PRIMARIES 50/60 Hz* †

Mfr. No.	Secondary		Insul. Test (Vrms)	Pri. (Volts)	Termination		Mtg. Style	Size (In.) H x W x D
	V	A			Pri.	Sec.		
P-8683	12.0CT	1.0	1500	115	Lugs	Lugs	S	2 3/4 x 3 1/2 x 2 1/2
P-8684#	12.0CT	1.0	1500	115	Lugs	Lugs	NH	2 1/2 x 3 x 2 1/2
P-8685#	18.0CT	1.0	1500	115	Lugs	Lugs	NH	3 1/4 x 3 1/4 x 3 1/4
P-8750	18.0CT	2.0	1500	115	Lugs	Lugs	NH	3 1/4 x 3 1/4 x 3 1/4
	32.0CT	.25	1500	115	Leads	Leads	A	2 1/4 x 3 3/4 x 1 1/4
	15.5CT	.75						

* May be operated from a 400 Hz source with no change in output ratings.

† Windings may be connected in series or parallel if properly phased. ALL SECONDARY VOLTAGES ±3%.

For 60 Hz only.

CONSTANT VOLTAGE LINE TO VOICE COIL TRANSFORMERS

Transformers with 70.7V constant voltage output. Lug terminations, except 8084, leads. Test Volts, 1000.

Mfr. No.	Mtg. Style	Impedance (Ohms)		Audio (Watts)
		Primary	Secondary	
A-8102	S	625/1250/2500 5000/10000	4/8/16	8/4/2 1/0.5
A-8103	S	312/625/1250 2500/5000/10000	4/8/16	16/8/4/2 1/0.5
A-8105	A	1000/2000/4000 8000/16000	4/8	5/2.5/1.25/ 0.62/0.31
A-8081	S	500/555/625/715/833	8/16	10/9/8/7/6
A-8084	A	1250/2500/5000 10000/20000/40000	8	4/2/1/0.5 0.25/0.12
A-8078	S	167/250/500/1000	4/8/16	30/20/10/5
A-8079	S	100/125/200/333	4/8/16	50/40/25/15

TELEPHONE COUPLING TRANSFORMERS

Mfr. No.	Fig.	Impedance (Ohms)		Pri. (mA DC)	Insertion Loss (dB)
		Primary	Secondary		
TTPC-1	A	600 CT	600 CT	0	1.4
TTPC-2	B	600	600	0	1.2
TTPC-3	B	600 CT	660 CT	0	1.2
TTPC-5	B	4000	600	0	1.5
TTPC-6	A	600	600 CT	90	1.8
TTPC-7	A	600	600	0	1.2
TTPC-8	A	600 CT	600 CT	0	1.2
TTPC-9	A	600	600/600	0	1.2
TTPC-11	A	4000	600	0	1.2
TTPC-13	F	600	600 CT split	90	1.8
TTPC-14	E	600	600 CT Split	80	1.1
TTPC-15	E	600	600	80	1.1
TTPC-19	G	600 CT	600 CT	80	2.2
PCT-27	D	600	600 CT 150 split	3	2.0
PCT-76	D	10000 CT	10000 CT	1	2.0
PCT-77	D	600 CT	600 CT	3	2.0
PCT-78	D	600	600	3	2.0

ENERGY-LIMITING TRANSFORMERS


Stancor P-591 Series are transformers whose winding impedance is such that with the primary energized at maximum rated voltage and frequency, and the secondary short circuited, secondary current will not exceed 8 amperes after one minute.

Mfr. No.	Volt-Amperes (VA)	Frequency (Hertz)	Primary Input (Volts)
P-591-900	30	50/60	120
P-591-901	30	50/60	240
P-591-902	30	50/60	208/240
P-591-910	40	50/60	120
P-591-911	40	50/60	240
P-591-912	40	50/60	208/240


Secondary Voltages: 24 VAC nominal.



Mtg. Style "A"



Mtg. Style "NH"



Mtg. Style "S"




Fig. A




Fig. B




Fig. C



Fig. D




Fig. E




Fig. F







Fig. G



MINIATURE, PLUG-IN PC POWER TRANSFORMERS




Mtg. Style "PC"



Mtg. Style "APC"

Mfr. No.	Mtg. Style	Secondary Rating		Size, Inches H x W x D
		Parallel	Series	
WITH 115 VOLT PRIMARY AND EQUAL SECONDARIES				
PPC-1	PC	4.0 V at 0.376 A	8.0 VCT at 0.188 A	1 1/8 x 1 1/32 x 1 1/32
PPC-2	PC	7.5 V at 0.2 A	15.0 VCT at 0.1 A	1 1/8 x 1 1/32 x 1 1/32
PPC-3	PC	15.0 V at 0.1 A	30.0 VCT at 0.05 A	1 1/8 x 1 1/32 x 1 1/32
PPC-4	PC	27.0 V at 0.056 A	54.0 VCT at 0.028 A	1 1/8 x 1 1/32 x 1 1/32
PPC-6	PC	58.0 V at 0.026 A	116.0 VCT at 0.013 A	1 1/8 x 1 1/32 x 1 1/32
PPC-7	PC	20.0 V at 0.076 A	40.0 VCT at 0.038 A	1 1/8 x 1 1/32 x 1 1/32
PPC-11	APC	4.0 V at 1.13 A	8.0 VCT at 0.562 A	1 1/2 x 2 3/8 x 1 1/4
PPC-12	APC	7.5 V at 0.6 A	15.0 VCT at 0.3 A	1 1/2 x 2 3/8 x 1 1/4
PPC-13	APC	15.0 V at 0.3 A	30.0 VCT at 0.15 A	1 1/2 x 2 3/8 x 1 1/4
PPC-14	APC	27.0 V at 0.168 A	54.0 VCT at 0.084 A	1 1/2 x 2 3/8 x 1 1/4
PPC-17	APC	20.0 V at 0.224 A	40.0 VCT at 0.112 A	1 1/2 x 2 3/8 x 1 1/4
PPC-22	APC	7.5 V at 1.0 A	15.0 VCT at 0.50 A	1 1/2 x 2 1/16 x 1 1/32
PPC-23	APC	15.0 V at 0.5 A	30.0 VCT at 0.25 A	1 1/2 x 2 1/16 x 1 1/32
PPC-27	APC	20.0 V at 0.376 A	40.0 VCT at 0.188 A	1 1/2 x 2 1/16 x 1 1/32
WITH 115/230 VOLT DUAL PRIMARIES AND EQUAL SECONDARIES				
PPC-8	PC	15.0 V at 0.1 A	30.0 VCT at 0.05 A	1 1/8 x 1 1/8 x 1 1/8
PPC-46	PC	7.5 V at 0.2 A	15.0 VCT at 0.1 A	1 1/8 x 1 1/8 x 1 1/8
PPC-51	PC	115.0 V at 0.013 A	230.0 VCT at 0.0065 A	1 1/8 x 1 1/8 x 1 1/8
PPC-18	APC	6.3 V at 0.7 A	12.6 VCT at 0.35 A	1 7/8 x 2 3/8 x 1 1/4
PPC-47	APC	7.5 V at 0.6 A	15.0 VCT at 0.3 A	1 7/8 x 2 3/8 x 1 1/4
PPC-19	APC	8.0 V at 0.56 A	16.0 VCT at 0.28 A	1 7/8 x 2 3/8 x 1 1/4
PPC-28	APC	10.0 V at 0.45 A	20.0 VCT at 0.225 A	1 7/8 x 2 3/8 x 1 1/4
PPC-20	APC	12.0 V at 0.36 A	24.0 VCT at 0.18 A	1 7/8 x 2 3/8 x 1 1/4
PPC-48	APC	15.0 V at 0.3 A	30.0 VCT at 0.15 A	1 7/8 x 2 3/8 x 1 1/4
PPC-56	PC	8.0 V at 3.0 A	16.0 VCT at 1.5 A	1 3/8 x 1 1/2 x 2 1/4
PPC-57	PC	10.0 V at 2.4 A	20.0 VCT at 1.2 A	1 3/8 x 1 1/2 x 2 1/4
PPC-58	PC	12.0 V at 2.0 A	24.0 VCT at 1.0 A	1 3/8 x 1 1/2 x 2 1/4

UNIVERSAL RECTIFIER TRANSFORMERS



Mtg. Style "NV"

Each transformer has the winding arrangement shown. The 117 VAC primary is connected to terminals 1 to 2, 3, or 4. The separate winding 5, 6, and 7 may be used in series with the primary to raise or lower the secondary voltage output. Transformers are designed for 50-60 Hz operation, but may also be operated at 400 Hz. Case style is NV with solder lug terminations. Rectifiers not included with transformers.


Mfr. No.	Range of Applied VAC Under Load	Max. DC Output				Filter Capacitor μ F
		Resistive or Induct Load		Capacitive Load		
		Volts	Amps	Volts	Amps	
RT-201	11.7-29.4*	11.2	2.0	13.8	2.0	1000
	11.1-28.5†	23.0	1.25	30.0	1.25	500
RT-202	12.0-29.8*	11.1	4.0	14.7	4.0	2000
	12.0-29.8†	24.3	2.0	33.0	2.0	1000
RT-204	11.7-29.2*	12.0	8.0	14.5	8.0	4000
	11.6-29.2†	24.0	4.0	32.4	4.0	2000
RT-206	12.0-29.7*	11.5	12.0	14.4	12.0	6000
	12.0-29.7†	24.0	6.0	32.0	6.0	3000
RT-208	12.1-29.2*	11.4	15.0	14.8	15.0	7500
	12.1-29.2†	23.7	8.0	32.5	8.0	4000
RT-2012	12.2-29.0*	11.4	22.5	14.3	22.5	12000
	12.2-29.0†	23.5	12.0	33.0	12.0	6000
RT-402	23.0-58.0*	25.0	4.0	33.5	4.0	3000
	23.0-58.0†	51.5	2.0	72.5	2.0	15000
RT-408	25.0-54.1*	23.4	12.0	32.0	12.0	4000
	25.0-54.1†	46.3	8.0	66.8	8.0	4000

*CT rectifier circuit. †Bridge rectifier circuit.

FILTER CHOKES



Mtg. Style "A2"



Mtg. Style "NH"



Mtg. Style "NV"

HIGH-CURRENT FILTER CHOKES

Inductance measured at 1 volt, 60 Hz. Insulation test voltage is twice allowable rms working voltage plus 1000 volts. Lead wire termination.

Mfr. No.	Inductance mH	DC Amps	DC Resis. Ohms	Insul. Test V _{rms}	Mtg. Style	Size, Inches H x W x D
TC-1	3.0	1.0	0.25	1000	A2	1 1/4 x 1 1/2 x 1 1/8
TC-2	11.0	1.0	0.75	1000	A2	1 1/4 x 1 1/2 x 1 1/8
C-2685	35.0	2.0	0.75	1500	NH	2 1/8 x 2 1/8 x 2 1/8
C-2686	25.0	4.0	0.43	1500	NH	2 1/8 x 3 1/8 x 2 1/8
C-2687	10.0	8.0	0.15	1500	NH	3 1/8 x 3 1/8 x 3
C-2688	10.0	12.5	0.11	1500	NH	3 1/8 x 4 1/8 x 3 1/8
C-2690	300	1.0	3.00	1500	NV	3 1/8 x 2 1/8 x 3
	or 75	2.0	.75			
	80	2.5	.60			
	or 20	5.0	.15			
C-2691				1500	NV	3 1/8 x 3 1/8 x 3 1/2

MINIATURIZED HIGH CURRENT CHOKES

Inductance measured at 1 volt 60 Hz.


Mfr. No.	Inductance mH	DC Amps	DC Resis. Ohms	Insul. Test V _{rms}	Mtg. Style	Size, Inches H x W x D
C-2722	400	.135	31.00	1500	A	1 1/4 x 2 1/8 x 1 1/8
C-2724	250	.275	16.00	1500	A	1 1/8 x 3/8 x 1 1/4
C-2728	75	1.000	2.50	1500	A	2 x 3/4 x 1 1/8

SMOOTHING CHOKES

Inductance tolerance—minus 15% plus 50% at 10 volts 60 Hz.

Mfr. No.	Inductance mH	DC Amps	DC Resis. Ohms	Insul. Test V _{rms}	Mtg. Style	Size, Inches H x W x D
C-1515	20.0	.015	900	1500	A	1 1/8 x 2 1/8 x 1 1/8
C-1706	4.5	.050	300	1500	A	1 1/8 x 2 1/8 x 1 1/8
C-1707	7.0	.050	550	1500	A	1 1/8 x 2 1/8 x 1 1/8
C-1709	8.0	.085	250	1500	A	2 x 3/4 x 1 1/8
C-2343	.75	.300	32	1500	A	1 1/8 x 2 1/8 x 1 1/8
C-1722	8.0	.300	80	3000	NV	4 1/8 x 3 1/8 x 1 1/8
C-2328	.8	.375	25	1500	A	2 1/8 x 3 1/8 x 1 1/8
C-2708	.32	.600	10	1500	A	2 x 3/4 x 1 1/8

AUTOTRANSFORMERS



Mtg. Style "C"

STEP-DOWN

Primaries 230 VAC, secondaries 115 VAC, 50/60 Hz. May be operated from a 400 Hz source with no change in output ratings. NEMA standard line cord and female receptacle.

Mfr. No.	Mtg. Style	VA	Size, Inches H x W x D	Wt. Lbs.
P-6287	C	40	3 1/4 x 2 1/2 x 2 1/2	2.2
P-8620*	A	50	2 1/4 x 3 1/4 x 1 1/4	1.5
GSD-75	C	75	3 1/4 x 3 1/4 x 2 1/4	3.0
P-8630	C	85	3 1/4 x 2 1/2 x 2 1/4	2.5
GSD-100	C	100	3 1/4 x 3 1/4 x 3	3.7
P-8631	C	125	3 1/4 x 2 1/2 x 3	3.0
GSD-150	C	150	3 1/4 x 3 1/4 x 3 1/4	4.4
P-8632	C	200	3 1/4 x 3 1/4 x 3 1/4	4.2
GSD-250	C	250	3 1/4 x 3 1/4 x 3 1/4	5.8
GSD-300	C	300	3 1/4 x 3 1/4 x 3 1/4	5.8
GSD-350	C	350	3 1/4 x 3 1/4 x 4 1/4	7.3
P-8634	C	400	3 1/4 x 3 1/4 x 4 1/4	7.0
GSD-500	C	500	4 1/4 x 3 1/4 x 4 1/4	10.6
GSD-750	C	750	4 1/4 x 3 1/4 x 5 1/4	14.4
GSD-1000	C	1000	4 1/4 x 3 1/4 x 6	17.0
GSD-1500	C	1500	5 1/4 x 4 1/4 x 6	20.0

*Has lead wires instead of cord and receptacle.

STEP-UP

Primaries 115 VAC, 50/60 Hz. May be operated from a 400 Hz. source with no change in output ratings. Three conductor line cord and receptacle. Case and core internally connected to third conductor of NEMA standard cord and receptacle for safety.

Mfr. No.	Mtg. Style	VA	Size, Inches H x W x D	Wt. Lbs.
P-8637	C	85	3 1/4 x 2 1/2 x 2 1/4	2.5
P-8638	C	125	3 1/4 x 2 1/2 x 3	3.0
P-8639	C	300	3 1/4 x 3 1/4 x 3 1/4	5.2
P-8640	C	500	4 1/4 x 3 1/4 x 4 1/4	10.3
P-8689	C	1000	4 1/4 x 3 1/4 x 6 1/4	17.0

STEP-DOWN AUTO-TRANSFORMER 230 V 50/60 Hz TO 115 V 50/60 Hz

Stancor step-down auto-transformers allow the use of equipment with an input rating of 115 V 50/60 Hz to be operated from 230 V 50/60 Hz outlets. More than one device may be operated by a single transformer providing the transformer selected has a capacity equal to or greater than the sum of the VA ratings or ampere ratings of the devices being operated.

Mfr. No.	VA	Amps
GSD-75	75	.65
GSD-100	100	.87
GSD-150	150	1.30
GSD-250	250	2.17
GSD-300	300	2.61
GSD-350	350	3.04
GSD-500	500	4.35
GSD-750	750	6.52
GSD-1000	1000	8.70
GSD-1500	1500	13.04

STEP-UP AUTO-TRANSFORMER 115 V 50/60 Hz TO 230 V 50/60 Hz

Stancor step-up auto-transformers allow the use of equipment with an input rating of 220-240 volts to be operated from 115 V 50/60 Hz outlets. More than one device may be operated by a single transformer providing the transformer selected has a capacity equal to or greater than the sum of the VA ratings or ampere ratings of the devices being operated.

Mfr. No.	VA	Amps
P-8637	85	.37
P-8638	125	.54
P-8639	300	1.30
P-8640	500	2.17
P-8689	1000	4.35

ISOLATION TRANSFORMERS



Mtg. Style "A"

Transformers have NEMA standard line cord for primary and female receptacle for secondary, except where noted.

Mfr. No.	Input Volts	Output Volts	Mtg. Style	VA	Size, Inches H x W x D
STRAIGHT ISOLATION					
GIS-100	115	115	C	100	3 1/4 x 2 1/4 x 3 1/4
GIS-150	115	115	C	150	3 1/4 x 3 1/4 x 4 1/4
GIS-250	115	115	C	250	4 1/4 x 3 1/4 x 4 1/4
GIS-500	115	115	C	500	4 1/4 x 3 1/4 x 6
GIS-1000	115	115	C	1000	5 1/4 x 4 1/4 x 8 1/4

STEP-DOWN ISOLATION
Case, core, and electrostatic shield internally connected to third conductor of line cord for safety.

Mfr. No.	Input Volts	Output Volts	Mtg. Style	VA	Size, Inches H x W x D
GISD-100	230	115	C	100	3 1/4 x 2 1/4 x 3 1/4
GISD-150	230	115	C	150	3 1/4 x 3 1/4 x 4 1/4
GISD-250	230	115	C	250	4 1/4 x 3 1/4 x 4 1/4
GISD-500	230	115	C	500	4 1/4 x 3 1/4 x 6
GISD-1000	230	115	C	1000	5 1/4 x 4 1/4 x 8 1/4

STRAIGHT ISOLATION
Electrostatic shield grounded to core.

Mfr. No.	Input Volts	Output Volts	Mtg. Style	VA	Size, Inches H x W x D
P-6413	115	115	A	0.6	1 1/4 x 2 1/4 x 1 1/4
P-6411	115	115	A	15	2 x 3 1/4 x 1 1/4
P-6412	115	115	A	35	2 1/4 x 3 1/4 x 2
P-6410	115	115	C	50	3 1/4 x 2 1/4 x 3 1/4
P-6160	105/115/125#	115	C	100	4 1/4 x 3 1/4 x 3 1/4
P-8622	115	115/230*	C	150	3 1/4 x 3 1/4 x 4
P-6161	105/115/125#	115	C	250	4 1/4 x 3 1/4 x 5 1/2

Mfr. No.	Input Volts	Output Volts	Mtg. Style	VA	Size, Inches H x W x D
P-6406*	115/230†‡	115	A	50	2 1/4 x 3 1/4 x 2 1/4
P-6385	210/230/250#	115	C	250	4 1/4 x 3 1/4 x 5 1/2

*Has lead wires. #Has selector switch. †Has electrostatic shield on separate leadwire (not grounded.) ‡Primary is two separate 115 volt windings. *Secondary is two separate 115 volt windings.



STEP-DOWN ISOLATION TRANSFORMER 230 V 50/60 Hz TO 115 V 50/60 Hz


Stancor step-down isolation transformers allow the use of equipment with an input rating of 115 V 50/60 Hz to be operated from 230 V 50/60 Hz outlets. They have the additional benefit of isolating the 115 V device from the 230 V line. More than one device may be operated from a single transformer providing the transformer selected has a capacity equal to or greater than the sum of the VA ratings or ampere ratings of the devices being operated.

Mfr. No.	VA	Amps
GISD-100	100	.87
GISD-150	150	1.30
GISD-250	250	2.17
GISD-500	500	4.35
GISD-1000	1000	8.70


"SIDE WINDER" SPLIT BOBBIN PC MOUNT POWER TRANSFORMERS

Case style, SW or DSW. UL recognized (E68100) CSA certified (LR67965).


Secondary Ratings		Size, Inches H x W x L	115 V Primary	115/230 V Primary
Series	Parallel		Mfr. No.	Mfr. No.
10.0 VCT at 0.11 A 10.0 VCT at 0.25 A 10.0 VCT at 0.6 A 10.0 VCT at 1.2 A 10.0 VCT at 2.0 A	5.0 V at 0.22 A 5.0 V at 0.5 A 5.0 V at 1.2 A 5.0 V at 2.4 A 5.0 V at 4.0 A	1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 2 $\frac{1}{4}$	SW-210 SW-310 SW-410 SW-510 SW-610	DSW-210 DSW-310 DSW-410 DSW-510 DSW-610
12.6 VCT at 0.09 A 12.6 VCT at 0.2 A 12.6 VCT at 0.5 A 12.6 VCT at 1.0 A 12.6 VCT at 1.6 A	6.3 V at 0.18 A 6.3 V at 0.4 A 6.3 V at 1.0 A 6.3 V at 2.0 A 6.3 V at 3.2 A	1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 2 $\frac{1}{4}$	SW-212 SW-312 SW-412 SW-512 SW-612	DSW-212 DSW-312 DSW-412 DSW-512 DSW-612
16.0 VCT at 0.07 A 16.0 VCT at 0.15 A 16.0 VCT at 0.4 A 16.0 VCT at 0.8 A 16.0 VCT at 1.25 A	8.0 V at 0.14 A 8.0 V at 0.3 A 8.0 V at 0.8 A 8.0 V at 1.6 A 8.0 V at 2.5 A	1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 2 $\frac{1}{4}$	SW-216 SW-316 SW-416 SW-516 SW-616	DSW-216 DSW-316 DSW-416 DSW-516 DSW-616
20.0 VCT at 0.055 A 20.0 VCT at 0.12 A 20.0 VCT at 0.3 A 20.0 VCT at 0.6 A 20.0 VCT at 1.0 A	10.0 V at 0.11 A 10.0 V at 0.24 A 10.0 V at 0.6 A 10.0 V at 1.2 A 10.0 V at 2.0 A	1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 2 $\frac{1}{4}$	SW-220 SW-320 SW-420 SW-520 SW-620	DSW-220 DSW-320 DSW-420 DSW-520 DSW-620
24.0 VCT at 0.045 A 24.0 VCT at 0.1 A 24.0 VCT at 0.25 A 24.0 VCT at 0.5 A 24.0 VCT at 0.8 A	12.0 V at 0.09 A 12.0 V at 0.2 A 12.0 V at 0.5 A 12.0 V at 1.0 A 12.0 V at 1.6 A	1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 2 $\frac{1}{4}$	SW-224 SW-324 SW-424 SW-524 SW-624	DSW-224 DSW-324 DSW-424 DSW-524 DSW-624
28.0 VCT at 0.04 A 28.0 VCT at 0.085 A 28.0 VCT at 0.2 A 28.0 VCT at 0.42 A 28.0 VCT at 0.7 A	14.0 V at 0.08 A 14.0 V at 0.17 A 14.0 V at 0.4 A 14.0 V at 0.84 A 14.0 V at 1.4 A	1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 2 $\frac{1}{4}$	SW-228 SW-328 SW-428 SW-528 SW-628	DSW-228 DSW-328 DSW-428 DSW-528 DSW-628
32.0 VCT at 0.035 A 32.0 VCT at 0.075 A 32.0 VCT at 0.188 A 32.0 VCT at 0.375 A 32.0 VCT at 0.625 A	16.0 V at 0.07 A 16.0 V at 0.15 A 16.0 V at 0.376 A 16.0 V at 0.750 A 16.0 V at 1.25 A	1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 2 $\frac{1}{4}$	SW-232 SW-332 SW-432 SW-532 SW-632	DSW-232 DSW-332 DSW-432 DSW-532 DSW-632
36.0 VCT at 0.03 A 36.0 VCT at 0.065 A 36.0 VCT at 0.17 A 36.0 VCT at 0.35 A 36.0 VCT at 0.55 A	18.0 V at 0.06 A 18.0 V at 0.13 A 18.0 V at 0.34 A 18.0 V at 0.7 A 18.0 V at 1.1 A	1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 2 $\frac{1}{4}$	SW-236 SW-336 SW-436 SW-536 SW-636	DSW-236 DSW-336 DSW-436 DSW-536 DSW-636
48.0 VCT at 0.023 A 48.0 VCT at 0.05 A 48.0 VCT at 0.125 A 48.0 VCT at 0.25 A 48.0 VCT at 0.4 A	24.0 V at 0.046 A 24.0 V at 0.1 A 24.0 V at 0.25 A 24.0 V at 0.5 A 24.0 V at 0.8 A	1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 2 $\frac{1}{4}$	SW-248 SW-348 SW-448 SW-548 SW-648	DSW-248 DSW-348 DSW-448 DSW-548 DSW-648
56.0 VCT at 0.02 A 56.0 VCT at 0.045 A 56.0 VCT at 0.11 A 56.0 VCT at 0.22 A 56.0 VCT at 0.35 A	28.0 V at 0.04 A 28.0 V at 0.09 A 28.0 V at 0.22 A 28.0 V at 0.44 A 28.0 V at 0.7 A	1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 2 $\frac{1}{4}$	SW-256 SW-356 SW-456 SW-556 SW-656	DSW-256 DSW-356 DSW-456 DSW-556 DSW-656
120 VCT at 0.01 A 120 VCT at 0.02 A 120 VCT at 0.05 A 120 VCT at 0.1 A 120 VCT at 0.16 A	60.0 V at 0.02 A 60.0 V at 0.04 A 60.0 V at 0.1 A 60.0 V at 0.2 A 60.0 V at 0.32 A	1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 1 $\frac{3}{8}$ 1 $\frac{1}{16}$ x 1 $\frac{1}{8}$ x 2 $\frac{1}{4}$	SW-2120 SW-3120 SW-4120 SW-5120 SW-6120	DSW-2120 DSW-3120 DSW-4120 DSW-5120 DSW-6120



Mtg. Style "SW"



Mtg. Style "DSW"



Mtg. Style "NV"

POWER SUPPLY TRANSFORMERS

For peripheral computer accessories. Produces positive and negative regulated DC voltages for op-amps and separate 5 to 6 volts for logic circuits. Terminations are lugs and transformers are rated to 105°C. Primaries are for 120 volts, 50-60 Hertz. Electrostatic shields are grounded internally to the core.

Mfr. No.	Case Style	Ratings		Size, Inches H x W x D
		Secondary No. 1	Secondary No. 2	
PCA-3	NV	33 VCT at 0.21 A	18 VCT at 1.25 A	3 $\frac{1}{2}$ x 2 $\frac{1}{2}$ x 2 $\frac{3}{8}$
PCA-4	NV	34 VCT at 0.35 A	19 VCT at 2.50 A	3 $\frac{7}{16}$ x 2 $\frac{1}{16}$ x 2 $\frac{7}{8}$

16

TRANSFORMERS & REACTORS