

ORDERING INFORMATION

Typical Part No. >	W	23	-X	1	A	1	G	-5															
<p>1. DESIGNATOR: W = Circuit breaker</p>																							
<p>2. SERIES NUMBER: 23 = Single pole, push/pull</p>																							
<p>3. CIRCUIT FUNCTION: X = Series trip</p>																							
<p>4. BUTTON: 1 = Black with white amp rate marking and white trip band.</p>																							
<p>5. MOUNTING BUSHING: A = 3/8"-24 threaded bushing .375" (9.53mm) long, silver color</p>																							
<p>6. TERMINALS (See drawings for relative terminal positions): 1 = Screw terminals situated 90° to each other with #8-32 screws and washers installed. 3 = Screw terminals situated parallel to each other pointing upward with #8-32 screws and washers installed.</p>																							
<p>7. MOUNTING HARDWARE: A = Knurled nut/hex nut installed G = Two hex nuts/lockwasher installed Z = No mounting hardware supplied</p>																							
<p>8. AMP RATING:</p> <table style="width:100%; border-collapse: collapse;"> <tr> <td style="width:10%;">0.5</td> <td style="width:10%;">3</td> <td style="width:10%;">7.5</td> <td style="width:10%;">20</td> <td style="width:10%;">35</td> </tr> <tr> <td>1</td> <td>4</td> <td>10</td> <td>25</td> <td>40</td> </tr> <tr> <td>2</td> <td>5</td> <td>15</td> <td>30</td> <td>50</td> </tr> </table>									0.5	3	7.5	20	35	1	4	10	25	40	2	5	15	30	50
0.5	3	7.5	20	35																			
1	4	10	25	40																			
2	5	15	30	50																			

STOCK ITEMS - The following items are normally maintained in stock for immediate delivery

W23-X1A1G-1	W23-X1A1G-7.50	W23-X1A1G-25	W23-X1A1G-50
W23-X1A1G-2	W23-X1A1G-10	W23-X1A1G-30	
W23-X1A1G-3	W23-X1A1G-15	W23-X1A1G-35	
W23-X1A1G-5	W23-X1A1G-20	W23-X1A1G-40	

ORDERING INFORMATION

Typical Part No. >	W	31	-X	2	M	1	G	-5															
<p>1. DESIGNATOR: W = Circuit breaker</p>																							
<p>2. SERIES NUMBER: 31 = Single pole, toggle actuator</p>																							
<p>3. CIRCUIT FUNCTION: X = Series trip</p>																							
<p>4. MOUNTING BUSHING: 1 = 15/32"-32 threaded bushing .320" (8.13 mm) long, round, silver color 2 = 15/32"-32 threaded bushing .320" (8.13 mm) long, double "D", silver color</p>																							
<p>5. TOGGLE: M = Silver color metal toggle, round, with amp rate marking on end</p>																							
<p>6. TERMINALS (See drawing for relative terminal positions): 1 = Screw terminals situated 90° to each other with #8-32 screws and washers installed. 5 = Screw terminals situated parallel to each other pointing downward with #8-32 screws and washers installed.</p>																							
<p>7. MOUNTING HARDWARE: A = Knurled nut/hex nut installed G = Two hex nuts/lockwasher installed Z = No mounting hardware supplied</p>																							
<p>8. AMP RATING:</p> <table style="width:100%; border-collapse: collapse;"> <tr> <td style="width:10%;">0.5</td> <td style="width:10%;">3</td> <td style="width:10%;">7.5</td> <td style="width:10%;">20</td> <td style="width:10%;">35</td> </tr> <tr> <td>1</td> <td>4</td> <td>10</td> <td>25</td> <td>40</td> </tr> <tr> <td>2</td> <td>5</td> <td>15</td> <td>30</td> <td>50</td> </tr> </table>									0.5	3	7.5	20	35	1	4	10	25	40	2	5	15	30	50
0.5	3	7.5	20	35																			
1	4	10	25	40																			
2	5	15	30	50																			

STOCK ITEMS - The following items are normally maintained in stock for immediate delivery

W31-X2M1G-1	W31-X2M1G-7.50	W31-X2M1G-25	W31-X2M1G-50
W31-X2M1G-2	W31-X2M1G-10	W31-X2M1G-30	
W31-X2M1G-3	W31-X2M1G-15	W31-X2M1G-35	
W31-X2M1G-5	W31-X2M1G-20	W31-X2M1G-40	