SLU-0200 Phase Monitor Relays (3-Phase Monitors) provide cost-effective protection against premature equipment failure caused by voltage faults on 3-Phase systems (Wye or Delta). The SLU-0200 Series multi-mode phase monitoring relay, was designed for the convenience of electrician's, maintenance managers and engineers. This device can be easily adjusted for the voltage, imbalance percentage and time delay requirements to protect against unbalanced voltages or single phasing regardless of any regenerative voltages.

Both **DELTA** and **WYE** systems may be monitored. In Wye systems, connections to neutral are NOT required. The SLU-0200 Series is UL Listed under UL File Number E55826.

NOTE: Can be used for most generator applications. Not recommended for variable frequency drive applications. Call technical support for application assistance.

AUTO	Frequency	Nominal Line-to-Line	Adjustable
RANGING		Voltages	Range
SCALES	60Hz	208, 220, 240, 380,	200-250
		415, 440, 460, 480	360-500
	50Hz	208, 220, 240	200-250
		346, 380, 415	330-430
VOLTAGE BAND	Drop-out	±10% of Range Settir	ng (Under/Over)
	Pick-up	±7% of Range Setting	g (Under/Over)
MAXIMUM	550 VAC (Lir	ne-to-Line)	
VOLTAGE			
PHASE	ABC (Will No	t Operate On CBA Sequen	
SEQUENCE		i operate on ebh sequen	
	00\/A Max		
POWER REQUIRED	90VA Max.		
PHASE		Adjustable Drop-out	
UNBALANCE	Hysteresis	10% of Setting	
PHASE SHIFT	13° Drop-out, 12° Pick-up (Ø-Loss)		
FREQUENCY	Not Detected	I	
SHIFT			
RAPID CYCLE	5 Cycle Lock	out, 30 minute cycle cour	it reset
	5 Cycle Lock Automatic	out, 30 minute cycle cour	it reset
RAPID CYCLE	Automatic	out, 30 minute cycle cour 240VAC Resistive, 1/2 H	
RAPID CYCLE RESET	Automatic	-	
RAPID CYCLE RESET RELAY OUTPUT	Automatic) 240VAC Resistive, 1/2 H	P @240VAC
RAPID CYCLE RESET RELAY OUTPUT	Automatic SPDT, 10A @ Normal (Green LED)	240VAC Resistive, 1/2 H Flashing Fault Delay Active	P @240VAC Continuous Relay Energized
RAPID CYCLE RESET RELAY OUTPUT	Automatic SPDT, 10A @ Normal (Green LED) Fault	240VAC Resistive, 1/2 H Flashing	P @240VAC Continuous Relay Energized Relay
RAPID CYCLE RESET RELAY OUTPUT	Automatic SPDT, 10A @ Normal (Green LED)	240VAC Resistive, 1/2 H Flashing Fault Delay Active	P @240VAC Continuous Relay Energized
RAPID CYCLE RESET RELAY OUTPUT	Automatic SPDT, 10A @ Normal (Green LED) Fault	240VAC Resistive, 1/2 H Flashing Fault Delay Active	P @240VAC Continuous Relay Energized Relay
RAPID CYCLE RESET RELAY OUTPUT INDICATORS	Automatic SPDT, 10A @ Normal (Green LED) Fault (Red LED)	2240VAC Resistive, 1/2 H Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustab	P @240VAC Continuous Relay Energized Relay De-energized
RAPID CYCLE RESET RELAY OUTPUT INDICATORS	Automatic SPDT, 10A @ Normal (Green LED) Fault (Red LED) Power Up	240VAC Resistive, 1/2 H Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustab 1 SEC. (Phase-Loss, U	P @240VAC Continuous Relay Energized Relay De-energized
RAPID CYCLE RESET RELAY OUTPUT INDICATORS	Automatic SPDT, 10A @ Normal (Green LED) Fault (Red LED) Power Up Fault Delay	2 240VAC Resistive, 1/2 H Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustab 1 SEC. (Phase-Loss, U Phase Reversal)	P @240VAC Continuous Relay Energized Relay De-energized Ile nbalance or
RAPID CYCLE RESET RELAY OUTPUT INDICATORS	Automatic SPDT, 10A @ Normal (Green LED) Fault (Red LED) Power Up Fault Delay	240VAC Resistive, 1/2 H Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustab 1 SEC. (Phase-Loss, U	P @240VAC Continuous Relay Energized Relay De-energized Ile nbalance or
RAPID CYCLE RESET RELAY OUTPUT INDICATORS	Automatic SPDT, 10A @ Normal (Green LED) Fault (Red LED) Power Up Fault Delay Severe Fault	2 240VAC Resistive, 1/2 H Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustab 1 SEC. (Phase-Loss, U Phase Reversal)	P @240VAC Continuous Relay Energized Relay De-energized Ile nbalance or
RAPID CYCLE RESET RELAY OUTPUT INDICATORS	Automatic SPDT, 10A @ Normal (Green LED) Fault (Red LED) Power Up Fault Delay Severe Fault Restart	2 240VAC Resistive, 1/2 H Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustab 1 SEC. (Phase-Loss, U Phase Reversal) 0.5 to 300 S, Adjustab	P @240VAC Continuous Relay Energized Relay De-energized Ile nbalance or ole (Auto Reset) -55°C)
RAPID CYCLE RESET RELAY OUTPUT INDICATORS RESPONSE	Automatic SPDT, 10A @ Normal (Green LED) Fault (Red LED) Power Up Fault Delay Severe Fault Restart Operate Storage	2 240VAC Resistive, 1/2 H Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustab 1 SEC. (Phase-Loss, U Phase Reversal) 0.5 to 300 S, Adjustab 32° to 131°F (0° to 4 -49° to 185°F (-45° t	P @240VAC Continuous Relay Energized Relay De-energized Ile nbalance or ole (Auto Reset) -55°C)
RAPID CYCLE RESET RELAY OUTPUT INDICATORS RESPONSE TEMPERATURE RATINGS	Automatic SPDT, 10A @ Normal (Green LED) Fault (Red LED) Power Up Fault Delay Severe Fault Restart Operate Storage	2 240VAC Resistive, 1/2 H Flashing Fault Delay Active Restart Delay Active 2.5 SEC Minimum 1 to 25 SEC., Adjustab 1 SEC. (Phase-Loss, U Phase Reversal) 0.5 to 300 S, Adjustab 32° to 131°F (0° to 4 -49° to 185°F (-45° t	P @240VAC Continuous Relay Energized Relay De-energized Ide nbalance or Ide (Auto Reset) -55°C) o +85°C)


IND. CONT. EQ


Universal Phase Monitor w/ Rapid Cycle Lockout

TOP LABEL

I ISTED

496Y





ORDERING INFORMATION

MODEL NUMBER	DESCRIPTION
SLU0200	Voltage/Phase Monitor

SLU-0200