PHASE LOSS, PHASE REVERSAL, PHASE UNBALANCE, UNDERVOLTAGE & OVERVOLTAGE **PMP-X SERIES**



- Additional SPNO contact for signaliong secondary systems
- Protects against phase loss, phase reversal, phase unbalance, undervoltage, overvoltage & rapid cycling
- Wide voltage ranges to cover more global applications
- True RMS voltage measurement ensures accurate sensing across more applications
- Retains fault indication and continues monitoring all voltages even with a lost phase
- Full fault indication on top of unit for easy troubleshooting
- Manual reset option works with external switch to reset the relay from outside the enclosure
- 5A SPDT + 5A SPNO contacts



MACROMATIC

Better. By Design.

800.238.7474 WWW.MACROMATIC.COM SALES@MACROMATIC.COM

The PMP-X Series Three-Phase Monitor Relays continuously monitor all voltages to protect motors and equipment from expensive damage due to phase loss, phase reversal, phase unbalance, undervoltage and overvoltage. These products detect single phasing and unbalanced voltages regardless of any regenerative voltages.

Utilizing an advanced microprocessor-based design allows true RMS voltage measurement with full wave monitoring. This provides a more accurate method to measure the voltages, regardless of load type or wave shape, and results in improved protection across more applications.

True RMS voltage measurement ensures accurate sensing in most generator and other applications with non-sinusoidal wave forms, eliminating nuisance tripping. Full wave monitoring provides a more accurate method to measure the voltages, regardless of load type or wave shape, resulting in improved protection across more applications.

Unlike similar three-phase monitor relays, the PMP-X Series will continue to function even with a lost phase. They are the only line-powered units in their class to retain fault indication and continuous monitoring of all voltages during a phase loss, increasing the ease of troubleshooting and the level of protection.

The PMP-X Series is a true universal product, with three units that work on a wide variety of adjustable line-line voltages to cover more global applications. Additional knobs allow adjustment of the undervoltage trip point, trip delay, restart delay and unbalance trip point. They utilize an industry-standard 8 pin octal socket.

The PMP-X series also provides an additional isolated SPNO contact that can be used for signaling separate PLC, SCADA, or alarm circuits or controlling secondary loads.

Operation:

When the proper 3-phase line voltage is applied to the unit and the phase sequence (rotation) is correct, the relay is energized after the Restart Delay is completed. Any one of five fault conditions will de-energize the relay after a delay. Re-energization is automatic upon correction of the fault condition. A bi-color status LED indicates normal condition and also provides specific fault indication to simplify troubleshooting (see "Status LED" on page 15).

PROTECTS AGAINST	MONITORED VOLTAGE▲ 50/60 Hz	CATALOG NUMBER	WIRING/SOCKET
Phase Loss, Phase Reversal,	102-138V	PMP120-X	8 Pin Octal 70169-D
Phase Unbalance, Undervoltage	190-500V	PMPU-X ● ■	ØA ØB ØC
& Overvoltage	460-600V	PMP575-X ●	
			*' †' DIAGRAM 175

- Phase-to-Phase (Line-to-Line).
- Requires a 600V-rated socket when used on system voltages above 300V. •
- Dual range unit auto-senses between the 190-250V AC and 350-500V AC ranges (see Application Data on next page).

PHASE LOSS, PHASE REVERSAL, PHASE UNBALANCE, UNDERVOLTAGE & OVERVOLTAGE PMP-X Series

Application Data

Voltage Requirements:

• •			
RANGE (50/60Hz ±5%)	MIN VOLTAGE	MAX VOLTAGE	CATALOG NUMBER
190-500V AC	156V AC	550V AC	PMPU
102-138V AC	77V AC	152V AC	PMP120
460-600V AC	345V AC	660V AC	PMP575

Three-Phase Line-Line Voltage:



The Voltage Line-Line knob on the PMPU-X has two ranges (left): a 190-250V low voltage scale and a 380-500V high voltage scale. The unit auto senses the three-phase line-line voltage when applied and automatically selects the appropriate range.

The PMP120-X has a single adjustable range of 102-138V and the PMP575-X has a single adjustable range of 460-600V.

Power Consumption: Less than 40VA.

Phase Loss: Unit trips on loss of any Phase A, B or C, regardless of any regenerative voltages.

Phase Reversal (Out-of-Sequence): Unit trips if sequence (rotation) of the three phases is anything other than A-B-C. It will not work on C-B-A.

Undervoltage: Adjustable from 80-95% of the line voltage setting. Unit trips when the average of all three lines is less than the adjusted set point for a period longer than the adjustable trip delay. It will reset at +3% of the Undervoltage trip setting.

Overvoltage: Fixed at 110% of the line voltage setting. Unit trips when the average of all three lines is greater than the fixed set point for a period longer than the adjustable trip delay. It will reset at 107% of the line voltage setting.

Phase Unbalance: Adjustable from 2-10% unbalance. Unit trips when any one of the three lines deviates from the average of all three lines by more than the adjusted set point for a period longer than the adjustable trip delay.

Response Times:		
Restart:		1 - 300 seconds adjustable
Drop-out Due to Faul	t:	-
Phase Loss and Re	versal:	100ms fixed
Undervoltage and C	Vervoltage:	0.3 - 30 seconds adjustable
Unbalance:		
Normal:		0.3 - 30 seconds adjustable
Severe (Twice Kr	ob Setting):	0.3 - 2 seconds
Output Contacts:	ontacts: SPDT + SPNO 5 A @ 277V AC / 5A @ 30V DC; 1/3HP @ 120/240V AC, B300 Pilot Duty	

Life: Mechanical: 10,000,000 operations; Full Load: 100,000 operations

Temperature: Opera	ating: -2	28° to 65°C (-18° to 149°F)	
Stora	ge: -4	0° to 85°C (-40° to 185°F)	

Mounting: Uses an 8 pin octal socket. Requires a 600V-rated socket when used on system voltages greater than 300V such as Macromatic Catalog Number 70169-D.

Status LED:

	LED STATUS	STATUS
GR		NORMAL (RELAY ON)
E N	MMMM	RESTART (DELAY)
		REVERSAL
RE	ſſ	LOSS/UB (UNBALANCE)
D		LOW VOLT (UNDERVOLTAGE)
		HIGH VOLT (OVERVOLTAGE)

Reset: The PMP-X Series relays reset automatically after completion of the restart delay.

115

File #F109466

Approvals:



Low Voltage & EMC Directives EN60947-1, EN60947-5-1

DIMENSIONS



All Dimensions in Inches (Millimeters)

800.238.7474 | www.macromatic.com | sales@macromatic.com