

Model List

MODEL 301:

Single preset counter with two inputs (one add, one subtract) and one output. Programmable features: preset value.

MODEL 302:

Dual preset counter with two inputs which are programmable for add/add, add/subtract, subtract/subtract or three quadrature modes and two outputs. Programmable features: count speed, prescale value, counting edge, decimal point, reset/preset function, output signal duration, preset values.

MODEL 303:

Dual preset counter and batch counter with two inputs which are programmable for add/add, add/subtract and subtract/subtract counting and two outputs. Programmable features: count speed, decimal point, output signal duration, reset/preset function, preset values.

MODEL 304:

Single preset counter and single preset batch counter with two inputs which are programmable for add/add, add/subtract and subtract/subtract counting and two outputs. Programmable features: count speed, decimal point, output signal duration, reset function, preset values.

MODEL 305:

Two independent, single preset totalizing counters and two outputs. Programmable features: count speed, decimal point, output signal duration, reset function, preset values.

MODEL 306:

Single preset teach-in counter and batch counter with two inputs (one add, one subtract) and one output. Via a front-panel button, the user "teaches" the device the preset value by pressing the button when the limit is reached.

MODEL 321:


Up/down preset hour meter with two programmable preset values, one control output and optical warning signal to indicate when second preset value is reached.

MODEL 322:

Dual hour meter with two programmable preset values and two control outputs. Programmable features: output signal duration, reset/preset function and preset values.

Model Encodement

Type Selection (order marking)



TYPE	POWER SUPPLY	INPUT VOLTAGE	OUTPUT TYPE	SENSOR POWER SUPPLY	COUNT FREQUENCY MODELS 301/306	COUNT FREQUENCY MODELS 302,3,4,5
01	230 VAC	AC	Relay	None	15Hz/15Hz	15 Hz
02	230 VAC	DC	Relay	24 VDC Unregulated	50Hz/1 kHz	Configurable
03	230 VAC	DC	Transistor	24 VDC Unregulated	50Hz/1 kHz	Configurable
04	120 VAC	AC	Relay	None	15Hz/15Hz	15 Hz
05	120 VAC	DC	Relay	24 VDC Unregulated	50Hz/1 kHz	Configurable
06	120 VAC	DC	Transistor	24 VDC Unregulated	50Hz/1 kHz	Configurable
07	24 VAC	AC	Relay	None	15Hz/15Hz	15 Hz
08	24 VAC	DC	Relay	24 VDC Regulated	50Hz/1 kHz	Configurable
09	24 VAC	DC	Transistor	24 VDC Regulated	50Hz/1 kHz	Configurable
10	24 VDC	AC	Relay	None	15Hz/15Hz	15 Hz
11	24 VDC	DC	Relay	None	50Hz/1 kHz	Configurable
12	24 VDC	DC	Transistor	None	50Hz/1 kHz	Configurable