


AUTOTRANSFORMERS



Mtg. Style "C"

STEP-DOWN

Primaries 230 VAC, secondaries 115 VAC, 50/60 Hz. May be operated from a 400 Hz source with no change in output ratings. NEMA standard line cord and female receptacle.

Mfr. No.	Mtg. Style	VA	Size, Inches H x W x D	Wt. Lbs.
P-6267	C	40	3 1/4 x 2 1/2 x 2 1/2	2.2
P-8620*	A	50	2 9/16 x 3 1/16 x 1 7/8	1.5
GSD-75	C	75	3 7/8 x 3 3/16 x 2 3/4	3.0
P-8630	C	85	3 1/4 x 2 1/2 x 2 3/4	2.5
GSD-100	C	100	3 7/8 x 3 3/16 x 3	3.7
P-8631	C	125	3 1/4 x 2 1/2 x 3	3.0
GSD-150	C	150	3 7/8 x 3 3/16 x 3 1/4	4.4
P-8632	C	200	3 7/8 x 3 1/8 x 3 1/4	4.2
GSD-250	C	250	3 7/8 x 3 3/16 x 3 3/8	5.8
GSD-300	C	300	3 7/8 x 3 3/16 x 3 3/8	5.8
GSD-350	C	350	3 7/8 x 3 3/16 x 4 1/8	7.3
P-8634	C	400	3 7/8 x 3 1/8 x 4 1/4	7.0
GSD-500	C	500	4 3/4 x 3 1/16 x 4 7/16	10.6
GSD-750	C	750	4 3/4 x 3 1/16 x 5 3/16	14.4
GSD-1000	C	1000	4 3/4 x 3 1/16 x 6	17.0
GSD-1500	C	1500	5 3/4 x 4 7/16 x 6	20.0

*Has lead wires instead of cord and receptacle.

STEP-UP

Primaries 115 VAC, 50/60 Hz. May be operated from a 400 Hz. source with no change in output ratings. Three conductor line cord and receptacle. Case and core internally connected to third conductor of NEMA standard cord and receptacle for safety.

Mfr. No.	Mtg. Style	VA	Size, Inches H x W x D	Wt. Lbs.
P-8637	C	85	3 1/4 x 2 1/2 x 2 3/4	2.5
P-8638	C	125	3 1/4 x 2 1/2 x 3	3.0
P-8639	C	300	3 7/8 x 3 1/8 x 3 3/8	5.2
P-8640	C	500	4 3/4 x 3 3/8 x 4 1/2	10.3
P-8689	C	1000	4 3/4 x 3 3/8 x 6 1/8	17.0

STEP-DOWN AUTO-TRANSFORMER 230 V 50/60 Hz TO 115 V 50/60 Hz

Stancor step-down auto-transformers allow the use of equipment with an input rating of 115 V 50/60 Hz to be operated from 230 V 50/60 Hz outlets. More than one device may be operated by a single transformer providing the transformer selected has a capacity equal to or greater than the sum of the VA ratings or ampere ratings of the devices being operated.

Mfg. No.	VA	Amps
GSD-75	75	.65
GSD-100	100	.87
GSD-150	150	1.30
GSD-250	250	2.17
GSD-300	300	2.61
GSD-350	350	3.04
GSD-500	500	4.35
GSD-750	750	6.52
GSD-1000	1000	8.70
GSD-1500	1500	13.04

STEP-UP AUTO-TRANSFORMER 115 V 50/60 Hz TO 230 V 50/60 Hz

Stancor step-up auto-transformers allow the use of equipment with an input rating of 220-240 volts to be operated from 115 V 50/60 Hz outlets. More than one device may be operated by a single transformer providing the transformer selected has a capacity equal to or greater than the sum of the VA ratings or ampere ratings of the devices being operated.

Mfg. No.	VA	Amps
P-8637	85	.37
P-8638	125	.54
P-8639	300	1.30
P-8640	500	2.17
P-8689	1000	4.35

ISOLATION TRANSFORMERS



Mtg. Style "A"

Transformers have NEMA standard line cord for primary and female receptacle for secondary, except where noted.

Mfr. No.	Input Volts	Output Volts	Mtg. Style	VA	Size, Inches H x W x D
STRAIGHT ISOLATION					
GIS-100	115	115	C	100	3 1/2 x 2 13/16 x 3 3/8
GIS-150	115	115	C	150	3 7/8 x 3 1/8 x 4 1/8
GIS-250	115	115	C	250	4 1/16 x 3 3/4 x 4 3/8
GIS-500	115	115	C	500	4 1/16 x 3 3/4 x 6
GIS-1000	115	115	C	1000	5 3/8 x 4 3/8 x 8 1/8

Case, core and electrostatic shield internally connected to third conductor of NEMA standard cord and receptacle for safety.

Mfr. No.	Input Volts	Output Volts	Mtg. Style	VA	Size, Inches H x W x D
STEP-DOWN ISOLATION					
GISD-100	230	115	C	100	3 1/2 x 2 13/16 x 3 3/8
GISD-150	230	115	C	150	3 7/8 x 3 1/8 x 4 1/8
GISD-250	230	115	C	250	4 1/16 x 3 3/4 x 4 3/8
GISD-500	230	115	C	500	4 1/16 x 3 3/4 x 6
GISD-1000	230	115	C	1000	5 3/8 x 4 3/8 x 8 1/8

Case, core, and electrostatic shield connected to third conductor of line cord for safety.

Mfr. No.	Input Volts	Output Volts	Mtg. Style	VA	Size, Inches H x W x D
STRAIGHT ISOLATION					
Electrostatic shield grounded to core.					
P-6413	115	115	A	0.6	1 1/4 x 2 1/8 x 1 1/4
P-6411	115	115	A	15	2 x 3 3/4 x 1 7/8
P-6412	115	115	A	35	2 3/8 x 3 3/4 x 2
P-6410	115	115	C	50	3 1/2 x 2 13/16 x 3 3/8
P-6160	105/115/ 125#	115	C	100	4 1/16 x 3 3/4 x 3 3/4
P-8622	115	115/ 230*	C	150	3 7/8 x 3 3/8 x 4
P-6161	105/115/ 125#	115	C	250	4 1/16 x 3 3/4 x 5 1/2

Mfr. No.	Input Volts	Output Volts	Mtg. Style	VA	Size, Inches H x W x D
STEP-DOWN ISOLATION					
P-6406*	115/230†‡	115	A	50	2 3/8 x 3 3/4 x 2 1/8
P-6385	210/230/ 250#	115	C	250	4 1/16 x 3 3/4 x 5 1/2

*Has lead wires. #Has selector switch. †Has electrostatic shield on separate leadwire (not grounded). ‡Primary is two separate 115 volt windings. *Secondary is two separate 115 volt windings.



STEP-DOWN ISOLATION TRANSFORMER 230 V 50/60 Hz TO 115 V 50/60 Hz

Stancor step-down isolation transformers allow the use of equipment with an input rating of 115 V 50/60 Hz to be operated from 230 V 50/60 Hz outlets. They have the additional benefit of isolating the 115 V device from the 230 V line. More than one device may be operated from a single transformer providing the transformer selected has a capacity equal to or greater than the sum of the VA ratings or ampere ratings of the devices being operated.

Mfg. No.	VA	Amps
GISD-100	100	.87
GISD-150	150	1.30
GISD-250	250	2.17
GISD-500	500	4.35
GISD-1000	1000	8.70