SINGLE ROW TERMINAL STRIPS

SERIES A1000 • SERIES CB1000
.325" Centers (8.26mm)

Series A1 is designed without standoffs for flush mounting; .025" standoffs available on the A1 Series as an option (suffix "-B"). Standoffs and side barrier standard on Series CB1000. Constructed of black, UL rated 94V0 thermoplastic. Rating: 15A;250V;UL/CSA. Screw: #6-32 zinc plated philslot. Wire Size: #14-22 AWG Cu. Distance between barriers: .260". Operating Temp: 150°F (65°C). Recommended PCB hole dia. of .070". IEC Compliance. Available with "Wire-Ready" option.

A1000 Series



CB1000 Series

A1/CB1 Series

Width = .50

Width = .60

A5/CB5 Series

Width = .43

Width = .50

SERIES A5000 • SERIES CB5000
.250" Centers (6.35mm)

Constructed of black, UL rated 94VO thermoplastic. Standoffs (.025") standard on both series. Space-saving design. Rating: 10A, 300V; UL/CSA. Screw: #3-48 zinc plated philslot. Wire Size: #16-30 AWG Cu. Distance between barriers: .200". Operating Temperature: 150°F (65°C) continuous. Recommended for PC board hole dia. of .062".

A5000 Series

CB5000 Series

"L" =	1000 Series	5000 Series
2 Pole: Barrier End Overall Length	0.720	0.560
2 Pole: Mount End Overall Length	1.370	1.060

Note 1. 1000 Series: Add .325 for each additional pole;
5000 Series: Add .250.
Note 2. For Mount End/Mount Centers: Determine desired overall length ("L") and subtract .390 for 1000 Series; subtract .310 for 5000 Series.
i.e., 1000 Series 4-pole "L" = 2.02 - .390 = 1.63 mount centers.
All dimensions in inches. For MM - multiply by 25.4.

Terminal Chart

(See Terminal Dimension Table)



01 Handwired



02 Circuit Board

03 Non Feed-Thru



04 Wire Wrap



07 Extended Pin

CB Terminal Exit Options:
CB1000 Series: Exit Rear (standard); "EF" Exit Front; "EB" Exit Back
CB5000 Series: Exit Rear (standard); "EF" Exit Front

Part Numbering System

□□□ Series	□□ Terminal	□ Base/End	□□ Poles
A1-standard barrier CB1-closed barrier A5-standard barrier CB5-closed barrier	See Terminal Chart 01-07	1-mount end 2-barrier end 3-closed base/ mount end	**1000 Series** 02-36 02-34 on mount end base **5000 Series** 02-30 02-28 on mount end base

Terminal Dimensions

Terminal Style	1000 Series A	1000 Series B	5000 Series A	5000 Series B
01	.425	.110	.400	.100
02	.135	.055	.170	.045
03	-	-	-	-
04	.325	.055	.400	.045
07	.515	.055	N/A	N/A

Toll Free 1-800-526-5376 • 201-337-1000 • Fax 201-337-1862