

(€¶1@



Wiring Diagram

TS441165



V = Voltage S1 = Initiate Switch L = Load

 $R_{T}\xspace$ is used when external adjustment is ordered.

Description

The TS441165 is an analog delay-on-make timer with a normally closed solid-state output. Unlike an interval timer, the load is energized prior to and during the time delay period. It can be used as a faster starting interval time delay when S1 is closed upon application of input voltage.

Operation (Delay-on-Make NC)

Upon application of input voltage, the load is energized immediately. When the initiate switch is closed, the time delay begins. At the end of the time delay, the load de-energizes.

Reset: When the initiate switch is reopened, the load again energizes and the time delay is reset. Removing input voltage resets the time delay and output.

Features & Benefits

FEATURES	BENEFITS		
Analog circuitry	Repeat Accuracy + / - 2%		
Compact, low cost design	Allows flexiblility for OEM applications		
1A steady, 10A inrush solid-state output	Provides 100 million operations in typical conditions.		
Load energized prior to and during time delay	Faster operation		
Totally solid state and encapsulated	No moving parts to arc and wear out over time and encapsulated to protect against shock, vibration, and humidity		
Normally closed output	Can be used as a faster starting interval time delay		

Accessories



P1004-XX, P1004-XX-X Versa-Pot

P1023-6 Mounting bracket

strain relief.

Panel mountable, industrial potentiometer recommended for remote time delay adjustment.



The 90° orientation of mounting slots makes installation/removal of modules quick and easy.



P0700-7 Versa-Knob Designed for 0.25 in (6.35 mm) shaft of Versa-Pot. Semi-gloss industrial black finish.



P1015-64 (AWG 14/16) Female Quick Connect These 0.25 in. (6.35 mm) female terminals are constructed with an insulator barrel to provide

P1015-18 Quick Connect to Screw Adapter Screw adapter terminal designed for use with all modules with 0.25 in. (6.35 mm) male quick connect terminals.

Time Delay Relays Dedicated - Delay-on-Make, Normally Closed



Accessories

TS441165



C103PM (AL) DIN Rail

35 mm aluminum DIN rail available in a 36 in. (91.4 cm) length.



P1023-20 DIN Rail Adapter

Allows module to be mounted on a 35 mm DIN type rail with two #10 screws.



VTP(X)(X) Plug-on Adjustment Module Mounts on modules with in-line adjustment terminals. Rated at 0.25W at 55°C. Available in resistance values from $5K\Omega$ to $5M\Omega$.

Selection Table for VTP Plug-on Adjustment Accessory

VTP P/N	

Selection Guide

R _T Selection Chart					
Des	Вт				
1	2	3	4	Megohm	
0.05	0.5	2	5	0.0	
0.5	10	30	60	0.5	
1.0	20	60	120	1.0	
1.5	30	90	180	1.5	
2.0	40	120	240	2.0	
2.5	50	150	300	2.5	
3.0	60	180	360	3.0	
			420	3.5	
			480	4.0	
			540	4.5	
			600	5.0	

When selecting an external R_T add at least 20% for tolerance of unit and the R_T

Function Diagram

DELAY-ON-MAKE (NORMALLY CLOSED)



Specifications

Time Delay Type Range Adjustment Repeat Accuracy Tolerance (Factory Calibration) Time Delay vs Temp. & Voltage Recycle Time Input Voltage Tolerance AC Line Frequency

Tolerance AC Line Frequency Output Type Form Maximum Load Current Voltage Drop Protection Circuitry Dielectric Breakdown Insulation Resistance Mechanical

Mounting Dimensions

Termination Environmental

Operating/Storage Temperature Humidity Weight Analog circuitry 165s Fixed ±2% or 20ms, whichever is greater; under fixed conditions

 $\leq \pm 10\%$

 $\leq \pm 10\%$

≤ 150ms

120VAC

±20% 50/60 Hz Solid state NC, closed during timing

NC, closed during timing 1A steady state, 10A inrush at 60°C ≅ 2.5V @ 1A

Encapsulated \geq 2000V RMS terminals to mounting surface \geq 100 M Ω

Surface mount with one #10 (M5 x 0.8) screw H 50.8 mm (2.0"); W 50.8 mm (2.0"); D 30.7 mm (1.21") 0.25 in. (6.35 mm) male quick connect terminals

 -40° to 75°C / -40° to 85°C 95% relative, non-condensing ≈ 2.4 oz (68 g)