




147 Central Avenue
 Hackensack, New Jersey 07601
 Tel: 201-489-8989 • Fax: 201-489-6911



CHICAGO MINIATURE LAMP, INC.
 WHERE INNOVATION COMES TO LIGHT

Electrical Industry Lamps

	Part Number	Operating Voltage	Design Watts	Initial MSCP	Average Life Hours	M.O.L. (inches)	Base
T-4 1/2 	6T4-1/2/120V	115-125	6.0	3.2	1,500	1.875	Candelabra Screw
	6T4-1/2/130V	130	6.0	3.2	1,500	1.875	Candelabra Screw
T-5 	10T5/120V	120	10.0	3.2	2,000	2.125	Candelabra Screw
S-6 	3S6/120V	120	3.0	.95	3,000	1.875	Candelabra Screw
	6S6/6V	6	6.0	4.3	1,500	1.875	Candelabra Screw
	6S6DC/6V	6	6.0	4.3	1,500	1.812	Double Contact Bayonet
	6S6/12V	12	6.0	4.3	1,500	1.875	Candelabra Screw
	6S6DC/12V	12	6.0	4.3	1,500	1.812	Double Contact Bayonet
	6S6/24V	24	6.0	4.3	1,500	1.875	Candelabra Screw
	6S6DC/24V	24	6.0	4.3	1,500	1.812	Double Contact Bayonet
	6S6/30V	30	6.0	4.0	1,500	1.875	Candelabra Screw
	6S6DC/30V	30	6.0	4.0	1,500	1.812	Double Contact Bayonet
	6S6S/40V	40	6.0	3.7	1,500	1.812	Single Contact Bayonet
	6S6/48V	48	6.0	3.7	1,500	1.875	Candelabra Screw
	6S6/60V	60	6.0	3.7	1,500	1.875	Candelabra Screw
	6S6DC/75V	75	6.0	3.7	1,500	1.812	Double Contact Bayonet
	6S6/120V	120	6.0	3.2	1,500	1.875	Candelabra Screw
	6S6N/120V	120	6.0	3.2	1,500	1.812	Intermediate Screw
	6S6S/120V	120	6.0	3.2	1,500	1.812	Single Contact Bayonet
	6S6DC/120V	120	6.0	3.2	1,500	1.812	Double Contact Bayonet
	6S6/130V	130	6.0	3.2	1,500	1.875	Candelabra Screw
	6S6/135V	135	6.0	3.0	1,500	1.875	Candelabra Screw
	6S6/145V	145	6.0	3.0	1,500	1.875	Candelabra Screw
	6S6DC/145V	145	6.0	3.0	1,500	1.812	Double Contact Bayonet
	6S6/155V	155	6.0	3.0	1,500	1.875	Candelabra Screw
	6S6S/155V	155	6.0	3.0	1,500	1.812	Single Contact Bayonet
	6S6DC/155V	155	6.0	3.0	1,500	1.812	Double Contact Bayonet
	10S6DC/230V	230	10.0	4.8	1,500	1.812	Double Contact Bayonet
10S6DC/250V	230	10.0	4.8	1,500	1.812	Double Contact Bayonet	

Chicago Miniature Lamp reserves the right to make specification revisions that enhance the design and/or performance of the product